



# Your Efficient Mono Laser Printer

Easy to set up and connect with  
fast flawless printing

**HL-L2442DW**



PRINT



WIRELESS

[www.brother.eu](http://www.brother.eu)

## Your Efficient Mono Laser Printer

Work smarter from anywhere at home or in the office with the easily connected Brother HL-L2442DW. Hosting a range of efficiency-boosting features, this mono laser printer saves you time with fast flawless printing, automatic 2-sided print, and a generous paper tray capacity. Get set up with ease and download the Brother Mobile Connect App, enabling you to print from virtually anywhere.

You will also benefit from a 3 year warranty upon product registration.

### HL-L2442DW



### Key features:

- Print up to 30 pages per minute
- 2-Sided print, up to 15 sides per minute
- 1 line LCD control panel
- 5GHz WiFi and USB
- 64MB Internal memory
- 250 Sheet paper input tray<sup>11</sup>
- Comes with 700 page yield toner
- 3,000 maximum yield available<sup>7</sup>

### Work smarter

The HL-L2442DW is designed to increase efficiency, with fast print speeds helping you to work smarter. The 2-sided print feature saves you time, enabling you to get on with other tasks.

### Effortless

Make your day easier and your printing effortless, with simple set up and 5GHz WiFi or USB connection. This efficient HL-L2442DW is a breeze to operate using the easy to navigate control panel.

### The perfect partner

High quality print technology ensures that your output is flawless and professional every time. The expertly designed HL-L2442DW has a high capacity paper input and output tray allowing you to print for longer, while the compact and quiet form enables you to work without interruption in smaller workspaces.

## Print longer

The HL-L2442DW keeps your printing costs down using a separate drum and toner unit, and the 700 pages<sup>7</sup> inbox toner supporting your higher print volume needs. Toner is easy to change and high yield toner is available, printing up to 3,000 pages<sup>7</sup>, reducing your cost per page and frequency to replace.

## Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The HL-L2442DW provides a range of robust features. It uses triple-layer security at a device, network and document level. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.

## Print from anywhere

With Brother Mobile Connect, you can fully operate your Brother printer from your fingertips. Print documents on the move and order genuine Brother supplies straight to your door. You can also personalise your frequently used features and unlock a revolutionary way of printing from your mobile device. Download the app on your mobile device to get started.



## General

### Technology

Electrophotographic  
Laser

### Memory

64MB

### Control panel

1 line LCD with  
keys

### Local Interface

Hi-Speed USB 2.0

### Wireless Network

2.4GHz and 5GHz  
Support

### Carton Contents

Device, Inbox Toner,  
Drum, Power Supply  
Cord, Quick  
Set-Up Guide, Warranty  
Card

## Print

### Print Speed (A4)

1 Sided: 30ppm Mono  
2 Sided: 15  
sides per minute  
Mono

### FPOT

#### (First Print Out Time)

Up to 8.5 Seconds Mono

### Quiet Mode

A mode to reduce the  
printing noise

### Resolution

Up to 1200 x 1200dpi

## Printer Functions

### N-up Printing

Reduce up to 25 pages  
into a single page

### Poster Printing

Enlarge a single page into  
a poster using 2x2, 3x3,  
4x4 or 5x5 pages

### Toner Save Mode

Use the Toner Save Mode  
to reduce toner  
consumption without  
affecting print speed

### Watermark Printing

Watermark your documents  
with predefined text,  
custom logo or custom  
messages

### ID Printing

Add identification to your  
printed documents (date and  
time, short custom message  
or  
PC username)

### Booklet Printing

Print documents in A5  
booklet format using  
automatic or manual 2-sided  
print

### Print Profiles

Store your favourite driver  
settings as profiles to  
easily recall them

### Manual 2-Sided Print

Manual 2-sided printing  
(recommended for media  
not supported by automatic  
2-sided print)

### Reverse Print

Rotate the content of a  
printed document by 180°

### Print Complete Notice

A printing notification can  
be set to go to your  
computer (Network only)

## Printer Driver

### Windows

Windows 11  
(32 and 64 bit  
editions) and more

### macOS

Printing via macOS requires  
the use of AirPrint. Mac drivers  
are not provided.

Visit [support.brother.com](https://support.brother.com) for the full list of supported OS  
and to download the latest drivers and software.

### Linux

CUPS, LPD/LPRng  
(x86/x64  
environment)

### ChromeOS

Supports native  
ChromeOS  
printing

## Paper Handling<sup>11</sup>

### Paper Input Standard Tray

250 Sheets

### Manual Feed Slot

1 Sheet

### Paper Output

150 Sheets A4

### Envelope Printing

Yes from manual feed slot

## Media Sizes

### Standard Tray

A4, Letter, B5(JIS), B5(ISO), A5, A5(Long Edge), B6(JIS), A6, Executive, A4 Short,

### Manual Feed Slot

Width 76.2 to 215.9 mm, Length 127 to 355.6 mm Envelope; COM-10, DL, C5, Monarch

### Auto 2-Sided

A4

## Media Type and Weights

### Standard Tray

Plain Paper, Thin Paper, Recycled Paper, Thick Paper 60-

### Manual Feed Slot

Plain Paper, Thin Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond, Label, Envelope, Env. Thin, Env. Thick

60-230gsm

### Auto 2-Sided

Plain Paper, Thin Paper, Recycled Paper 64-105gsm

## Mobile and Web Connectivity

### Brother Mobile Connect<sup>17</sup> (Android)

Print from and check the machine status from an Android device

### Brother Mobile Connect<sup>17</sup> (iPad / iPhone)

Print from and check the machine status from an iPad / iPhone

### Apple AirPrint<sup>17</sup>

Print from and scan to most common file types from any AirPrint enabled application

### Brother Print Service Plugin<sup>17</sup>

Print from an Android devices without a dedicated App.

### Mopria™<sup>17</sup>

Print most common file types from Mopria™ supported Android devices

## Fleet Management Tools

### BRAdmin<sup>16,17</sup>

LAN/WAN management software

### Embedded Web Server

Web based print management software embedded onto the device

### Driver Deployment Wizard<sup>16,17</sup>

Easily create print drivers for hassle free deployment over your network

### Status Monitor<sup>16</sup>

Monitor the status of your machine from your computer

## Software

### Brother iPrint&Scan Desktop<sup>15,17</sup>

Print from and check the machine status from Windows or macOS PC

### Utilities

Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

### Easy Setup

Simple access to drivers and software for the installation of your Brother machine from support.brother.com Windows/Mac

## Connectivity

### Wireless Network

2.4GHz: IEEE 802.11 b/g/n  
(Infrastructure Mode)  
IEEE 802.11 g/n (Wi-Fi  
Direct)  
5GHz: IEEE 802.11 a/n  
(Infrastructure Mode)  
IEEE 802.11 a/n (Wi-Fi  
Direct)

### Wi-Fi Direct®

Print wirelessly without having  
to go through a wireless  
access point (both automatic  
and manual methods  
supported)

### Wireless Setup Support

Wi-Fi Protected Setup  
(WPS))

### Wireless Applications

Vertical Pairing

### Mobile

Print or scan from your  
mobile device with Brother  
Mobile Connect, Airprint,  
Mopria

### Local Interface

Hi-Speed USB 2.0

## Security Features

### Wireless Network Security

WEP 64/128 bit, WPA-PSK  
(TKIP/AES), WPA2-PSK (TKIP/  
AES), WPA3-SAE (AES), WIFI  
Direct supports WPA2-  
PSK (AES) only.

SMTP-AUTH, SNMP v3, SSL/  
TLS(SMTP,HTTP,IPP), 802.1x  
(EAP-FAST, PEAP, EAP-TLS,  
EAP-TTLS), OAuth(SMTP,  
POP3, IMAP4)

### IPv4

ARP, RARP, BOOTP, DHCP,  
APIPA(Auto IP),  
WINS/NetBIOS  
name resolution, DNS  
Resolver, mDNS, LLNMR  
responder, LPR/LPD, Custom  
Raw Port/Port9100, SMTP  
Client, IPP/ IPPS, FTP Server,  
SNMPv1/v2c/v3, HTTP/HTTPS  
server, TFTP client and server,  
ICMP, Web Services (Print)

### IPv6

NDP, RA, DNS resolver,  
mDNS, LLNMR responder,  
LPR/LPD, Custom Raw  
Port/Port9100, IPP/IPPS,  
SMTP Client, FTP  
Server, SNMPv1/v2c/v3,  
HTTP/  
HTTPS server, TFTP client  
and server, ICMPv6, Web  
Services (Print)

### IP Filter

Restrict which network users  
can or cannot access the  
device over the network (IPv4  
only)

### E-mail Notifications

Automatically have the device  
send e-mail alerts when it  
requires attention, such as  
when the toner is low or  
needs replacing

### E-mail Reports

Receive usage reports on  
a regular basis via e-mail

### Automatic Intrusion Detection

All Brother Print devices are  
secure by design. Devices  
automatically recognise  
security attacks and take  
preventative measures,  
including rebooting where  
necessary, to ensure the  
device remains secure

### Firmware Updates

In addition to allowing  
automatic update alerts to  
install the latest version the  
printer can be set  
to not receive older firmware  
versions to avoid downgrade  
by an unauthorised user

### Certificate Management

Use the default standard  
self-signed, create a  
custom  
self-signed certificate, certificate  
signing request (CSR), or  
external public certificate &  
private key for protected  
network communication  
**Digitally-signed Firmware**  
The firmware for Brother print  
and scan devices is digitally  
signed and secure

### Port-based Network Access Control

(IEEE 802.1x)  
Brother devices are in full  
compliance with this standard,  
to allow connection to an  
802.1x EAP (Extensible  
Authentication Protocol)  
protected network  
**Restrict network protocols**  
The Protocol Control feature  
allows an administrator to  
restrict communication protocols  
(e.g. FTP, Telnet) as required

## Supplies and Consumables

**Inbox Toner<sup>7</sup>**  
1 x 700 pages (BK)

**High Yield Toner<sup>7</sup>**  
TN2590XL - 3,000 pages

**Drum Unit**  
DR2590 Approx 15,000  
pages at 1 pages per job

**Standard Yield Toner<sup>7</sup>**  
TN2590 - 1,200 pages

## Dimensions and Weights

**With Carton (WxDxH)**  
438 x 283 x 519mm - 8.20kg

**Without Carton (WxDxH)**  
356 x 360 x 183mm - 6.00kg

## Duty Cycle

**Recommended Monthly**  
Up to 2,500 pages

## Operating Environment

**Power Requirement**  
220-240V  
AC 50/60Hz

**Operating Environment**  
Humidity 20 - 80 %  
10°C - 32.5°C  
50°F - 90.5°F

**Storage Environment**  
Humidity 35 - 85 %  
0°C - 40°C  
32°F - 104°F

## Environment

**Approx Power Consumption<sup>13,23</sup>**  
Printing: 440W  
Printing in quiet mode:  
270W Ready: 43W  
Sleep: 3.8W  
Deep Sleep:  
0.6W Power Off:  
0.08W

**TEC Value**  
0.34 kWh/week

**Sound Power<sup>12</sup>**  
Printing: 6.56B(A)  
Ready: Inaudible  
Quiet Mode:  
6.06B(A) Deep  
Sleep: Inaudible

**Sound Pressure<sup>12</sup>**  
PC Printing (Mono):  
Approx. 48.0dB(A)  
Ready: 30.0db(A)  
Quiet Mode:  
44.0db(A)

**Toner Save**  
This reduces the toner  
consumption to get more pages  
from your consumables

- 3 Scan Speeds based on ISO/IEC 17991
- 7 Approx. declared yield value in accordance with ISO/IEC 19752
- 11 Capacity calculated with 80gsm paper
- 12 Sound pressure and sound power level in accordance with ISO 7779
- 13 Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15 Windows and macOS only
- 16 Windows only
- 17 Optional download
- 18 Requires an Internet connection
- 23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration



**Working with you for a better environment**

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

[www.brotherearth.com](http://www.brotherearth.com)

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

